

## COMmanner® S<sub>2M</sub> module

Expansion module for connecting the COMmanner Basic.2, Business and COMmanner 6000 series on a primary rate interface (PRI) with up to 30 B channels to the exchange.

- 1 PRI connection with up to 30 channels to the public exchange office
- Connection via detachable screw terminal and RJ-45 jack
- Passive connection for test equipment
- Channels can be configured directionally (outgoing, incoming or incoming and outgoing)
- Configurable number of channels in use
- LEDs to indicate different operation states
- NTPM power supply possible via the module



The COMmanner S<sub>2M</sub> Module expands the COMmanner Basic.2, Business and COMmanner 6000 series by one PRI port for the connection of a primary rate interface with up to 30 B channels from the network provider. The channels can be configured directionally (outgoing, incoming or incoming and outgoing).

### Features

- PRI connection with up to 30 channels to the public office
- Connection via detachable screw terminal and RJ-45 jack
- Passive connection for test equipment
- Channels can be configured directional (outgoing, incoming or incoming and outgoing)
- Configurable number of the channels in use
- LEDs for the signalling of different operation states
- Power supply of the NTPM via the module possible

### Supported Auerswald ICT systems

#### S<sub>2M</sub> Module

- COMmanner Basic
- COMmanner Basic.2
- COMmanner Basic.2 19" (BA-S2M necessary)
- COMmanner Business
- COMmanner Business.2 19" (BU-S2M necessary)
- COMmanner 6000

#### S<sub>2M</sub> R-Module

- COMmanner 6000R
- COMmanner 6000RX

### Technical data

- **Operation voltage:** out of the COMmanner base unit
- **Installation:** slot in the housing of the COMmanner
- **Trunk lines:** 1 PRI port, PTP connection (Euro-ISDN, DSS-1)
- **Dimensions** (W x H x D): 293 mm x 97 mm x 16 mm (S<sub>2M</sub>), 25 mm x 261,8 mm x 143,5 mm (S<sub>2M</sub>-R)
- **Weight:** approx. 105 g (S<sub>2M</sub>), approx. 162 g (S<sub>2M</sub>-R)
- **Security:** CE

### Scope of delivery

- COMmanner S<sub>2M</sub> Module or S<sub>2M</sub> R-Module

### Order information

- **Name:** COMmanner S<sub>2M</sub>-Modul
- **Article number:** 16426
  
- **Name:** COMmanner S<sub>2M</sub>-R-Modul
- **Article number:** 16674

Copyright © 2018 Auerswald GmbH & Co. KG  
Version 5.0 - Subject to modifications