

TSA-a/b



Adapter for connecting 4-wire or FTZ door phones to an analogue port of modern ICT systems



- Access of older door phone systems with up to 2 bell buttons to an analogue port of a modern ICT system
- Inverter from 4-wire and FTZ 123 D 12-0 interface to analogue subscriber ports
- Additional switching options via optional a/b Switching Modules
- Power supply via bell transformer
- Separate volume control for both speech channels, impedance adjustable

Your advantages in detail

The conversion of telephony to IP often involves purchasing a new ICT system. Although these modern systems are state-of-the-art and offer all sorts of modern features, you will not find a connection for the existing door phones anywhere. Here's the solution:

With the TSA-a/b door phone adapter, door terminals with an older 4-core interface or a 2-core connection in accordance with FTZ 123 D 12-0, which perhaps

cannot be easily replaced for structural reasons, can be connected to the analogue port of a modern, VoIP-enabled ICT system. The existing door terminal, from Siedle, Ritto, Grothe or Auerswald/FONtevo for example, can be kept.

The TSA-a/b is suitable for use on all conventional ICT systems with analogue subscriber ports.

TSA-a/b

Features at a glance

TECHNICAL SPECIFICATIONS

Connections

- Power supply: bell transformer, 8 V – 12 V AC or 12 V – 40 V DC, 0.5 A max.
- System connection: analogue subscriber port of an ICT system
- Door phone connection: 4 wire system or FTZ 123 D 12-0 interface (e.g. Siedle, Ritto, Grothe), power supply 9 V / 12 V DC, 200 mA (can be selected)
- Bell button: 2 max., dry contact
- Door opening relais: 8 V – 12 V AC, 12 V – 40 V DC, 2 A

- Light relaiy: 8 V – 12 V AC, 12 V – 40 V DC, 1 A
- Casing material: plastic, grey
- Dimensions (w x h x d): 142 mm x 81 mm x 27 mm
- Weight: 136 g
- Compliance: CE

DELIVERY

- Door phone adapter TSA-a/b
- Mounting material
- Setup guide

ORDERING INFORMATION

Designation: TSA-a/b

Article number: 90060

EAN Code: 4019377900604